



DYNAVATION
ELECTRONICS

®

DT-606A+

DIGITAL CLAMPMETER

Features:

- Digital Clamp meter 5999 counts AC/DC 600V 600A Clamp multimeter with Live NCV Flashlight True-RMS function.
- It can be used to measure such parameters as DCV, ACV, DCA and ACA, Resistance, Continuity Buzzer, Diode, Frequency etc.
- This meter is a handheld automatic range digital multimeter which driven by battery.
- Open jaws: 35mm

Function	Range	Accuracy
DC-Voltage	600mV/6V/60V	±(0.5%+3)
	600V	±(0.5%+3)
AC-Voltage	6V/60V	±(0.8%+5)
	600V	±(0.8%+5)
ACA	6A/60A	±(0.5%+3)
	600A	±(0.5%+3)
CAPACITANCE	6nF/60nF/600nF/6uF	±(0.5%+3)
	60uF/600uF/6mF	±(0.5%+3)
LOW INPEDANCE ACV	6V/60V/300V	±(0.5%+3)
FREQUENCY	10Hz/100Hz/1kHz/10kHz/ 100kHz/ 1MHz/10MHz	±(0.3%+3)

Special Function:

Resistance	600Ω/6kΩ/60kΩ/ 600kΩ/6MΩ/20MΩ/60MΩ	±(1.0%+2)
Display method	LCD display 5999 count	
Diode measurement	YES	
Data retention	YES	
NCV measurement	YES	
Fire detection	YES	
Low voltage warning	YES	
Flashlight lighting	YES	
True effective value	YES	
Max/Min	About 10MΩ	
Low Z	3 times/s	
Shock proof protection	YES	
AC frequency response	50-60Hz	
Sampling rate	3 times/s	
Operation way	Manual/Auto range	
Max. Display	5999	
Clamp Size	35mm	
Battery	Two AAA batteries	
Polarity	Automatic polarity display	
Product Color	Case: black ; Holster color:orange	
Product Net Weight	Approx 236g	
Product Dimension	207*72*39mm	
Standard Accessories	Test leads , battery ,instruction manual	



1 YEAR WARRANTY

QUALITY GUARANTEED

* All Specifications & appearances are subject to change without prior notice.

www.dynavationelectronics.com