

## **DT-9205C** DIGITAL MULTIMETER

## **Features:**

- New type holster, streamline design.
- Large LCD makes the reading clearly.
- Metallic screen board with stronger antimagnetic and anti-interferential function.
- Full function protection, anti-high voltage circuit design.
- Full function protection, anti-high voltage circuit design.

Function	Range	Accuracy
DC-Voltage	200mV/6V/60V/600V	±(0.5%+3)
	1000V	±(0.5%+3)
AC-Voltage	2V/20V/200V	±(0.8%+5)
	750V	±(0.5%+3)
DC-Amp	200µA/6000µA/60mA	±(0.5%+3)
	600mA/10A	±(0.5% <mark>+3)</mark>
AC-Amp	200µA	±(0.5 <mark>%+3)</mark>
	10A	±(0. <mark>5%+3)</mark>



200Ω/6kΩ	±(1.0%+3)	
60kΩ /600kΩ	±(1.0%+3)	
20ΜΩ/200ΜΩ	±(1.5%+3)	
20nF	±(4%+5)	
2uF	±(4%+5)	
200uF	±(4%+5)	
-20°C~1000°C -4°F~ 1832°F		
	YES	
YES		
	YES	
	10Hz ~ 1kHz	
	Battery 2*1.5V AA	
Auto National Auto	Case: black ; Holster color:orange	
	Approx . 358g (including battery)	
	178*86*52mm	
	Test leads,battery,manual	
	60kΩ /600kΩ 20MΩ/200MΩ 20nF 2uF	

